

Programmer

MKP 1

- Remote powered from the device







Model
Art. No.

MKP 1
812900

Programmable Multiband Amplifier

MKVP 701

- Selective frequency range inputs
- Fully compatible with digital TV signals
- Automatic digital/analogue signal identification
- AES Automatic equalization of output level
- AUX input for channels processed by other units
- Adjust input initial and final channels, gain, output level, UHF-AGC, etc. using MKP 1



Model Art. No.	MKVP 701 812150						
Inputs	FM	B I	B III / DAB	AUX	UHF 1	UHF 2	UHF 3
Bandwidth MHz	87,5 - 108	47 - 68	174 - 230	47 - 68 130 - 862	470 - 862		
Number of amplifiers	1				10		
Filter bandwidth	fixed				variable: 1-6 channels		
Configuration of amplifiers per input	no				6	4	0
	no				6	3	1
	no				10	0	0
	no				9	0	1
Gain in dB	40			23	53		
Input regulation	0	25	23	no	23		
Output regulation	25	20					
Noise figure in dB	6		8	15	8		
Operating input level	71 / 101	70 / 95	70 / 93	90	60 / 83		
Mains supply U~	230 V ± 5%						
Remote powering	24 V / 100 mA						
Operating temperature	0 ... +50 °C						
Dimensions (mm)	350 x 250 x 60						